Product family datasheet

# **OSRAM**

# **DIADEM CHROME**

Only amber during operation





Chrome design Thanks to cutting edge interference and absorber coating



Amber when ON Only amber when operating, otherwise almost invisible



Homogenous appearance Reflector has a fully homogenous chrome look





OSRAM DIADEM CHROME signal lamps have a strikingly exclusive design: their chrome look made possible by a cutting edge interference and absorber coating. The lamps emit amber light only when operational. At other times, they are almost invisible and have no irritating color effects. DIADEM CHROME lamps are ideal for all indicator lights with clear covers.

## Product family datasheet

### Technical data

	Electrical Data				Photometric Data	
Product description	Power input	Nominal voltage	Nominal wattage	Test voltage	Nominal luminous flux	
DIADEM CHROME PY21W	25 W	12 V	21 W	13.5 V	280 lm	
DIADEM CHROME WY5W <sup>1)</sup>	5 W	12 V	5 W	13.5 V	30 lm	

		Physical Attributes & Dimensions		Lifetime Data		Certificates & standards
Product description	Luminous flux tolerance	Diameter	Diameter	Lifespan B3	Lifespan Tc	ECE category
DIADEM CHROME PY21W	±20 %	25.0 mm	25.0 mm	100 hr	250 hr	PY21W
DIADEM CHROME WY5W <sup>1)</sup>	±20 %	10.0 mm	10.0 mm	200 hr	500 hr	WY5W

	-	Environmental & Regulatory Information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)				
Product description	Primary article identifier	Candidate list substance 1	Declaration no. in SCIP database			
DIADEM CHROME PY21W	4052899418011   4008321972774   4062172211529   4062172394857   4052899241657   4052899417977	No declarable substances contained	No declarable substances contained			
DIADEM CHROME WY5W <sup>1)</sup>	4052899417939   4052899979925   4008321972750   4052899417915   4062172394758   4052899417953   4052899067790	No declarable substances contained	No declarable substances contained			

 $^{1)}\,\mathrm{Amber}$  lamp for clear indicators

## Product family datasheet

#### Download Data

 File

 User instruction
 GPRS\_Safety symbols instructions

### Application advice

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.





0'0





